

# PRODUCT DATASHEET Smart+ Wifi Flex Magic RGB 5M Remote Control

SMART+ WIFI MAGIC RGB FLEX WITH REMOTE CONTROL | Decorative LED Strips with WiFi technology and MAGIC RGB



# Areas of application

- Living areas
- Indirect lighting

### **Product benefits**

- Easy and quick installation
- Magic RGB Color Control for maximum flexible selection

# Product features

- Dimmable
- RGB color control, approx. 16 million color options adjustable
- DIY function: You can adjust the color segment per segment and create your own lighting scenes or just use already available lighting scenes
- Flexible, bendable LED strips
- Controllable via SMART+ App (with minimum Android 8.0 or iOS 14.0)

# TECHNICAL DATA

# Electrical data

Nominal wattage	24.00 W
Nominal voltage	220240 V
Nominal current	130.000 mA
Mains frequency	5060 Hz
Power factor $\lambda$	> 0.50

## Photometrical data

Light color (designation)	Red / Green / Blue
Standard deviation of color matching	< 6 sdcm

# Light technical data

Beam angle	120°
Starting time	< 0.5 s

# Dimensions & Weight

Product weight	330.00 g
Length	5000.00 mm
Width	10.00 mm
Height	3.00 mm

# Lifespan

Number of switching cycles	15000
Lifespan	30000 h

# Colors & materials

Product color	White
Housing color	White
Body material	Polyurethane (PU)

# Temperatures & operating conditions

Ambient temperature range	-20+40 °C

# Additional product data

Product remark	Reset settings to default by switching the product on for three seconds and off for three seconds and repeating this five times.		
Capabilities			
Dimmable	Yes		
Type of connection	Plug type C (EU)		
BATTERY			
Battery size [GMS]	CR2025		
Certificates & Standards			
Standards	CE		
Protection class	II II		
Type of protection	IP20		

### **EQUIPMENT / ACCESSORIES**

- Control via app or voice control requires compatible Smart home system
- Complete mounting and connecting accessories included
- Remote control and battery included
- For control via SMART+ App, a smartphone or tablet is required (with minimum Android 8.0 or iOS 14.0)

# Safety advice

- To reduce the risk of strangulation the flexible wiring connected to this luminaire shall be effectively fixed to the wall if the wiring is within arm's reach
- Battery Warning: Keep out of reach for children. Swallowing can lead to chemical burns, perforation of soft tissue, and death. Severe burns can occur within 2 hours of ingestion. Seek medical attention immediately.
- If the battery compartment (if applicable) does not close securely, stop using the product and keep it away from children. If you think batteries might have been swallowed or placed inside any part of the body, seek immediate medical attention.
- Please avoid: Maximal ambient temperature: +35 °C. Replacement of a battery with an incorrect type that can defeat safeguard (for example, in the case of some lithium battery types). Altitude during operation: 2000 m. Disposal of a battery into fire or a hot oven, or mechanically crushing or cutting of a battery, that can result in an explosion.
- Do not connect the rope light to the supply while it is wound onto a reel. Do not use the lightstrip when covered or recessed into a surface. The string of lights may not be operated within the packaging. Do not open the lightstrip.

### **DOWNLOAD DATA**

Documents and certificates		Document name	
PDF	User instruction / safety instructions	SMART WIFI FLEX Magic RGB	
PDF	Legal information	Safety insert G11226722	
PDF	Declarations of conformity	SMART WIFI FLEX 3M AND 5M	

Documents and certificates Docume		Document name
POF	EU Data Act	SMART WiFi Lamps and Luminaires

## LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4099854483127	Folding box	67 mm x 167 mm x 168 mm	388.00 g	1.88 dm <sup>3</sup>
4099854483134	Shipping box 4	350 mm x 185 mm x 155 mm	1804.00 g	10.04 dm <sup>3</sup>

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

## References / Links

- Further information and frequently asked questions (FAQs) at www.ledvance.com/en-int/home-lighting/services/faq

## **DISCLAIMER**

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.