

PRODUCT DATASHEET SMART+ MATTER Orbis Downlight Round 400mm Tunable White

SMART+ MATTER Surface Downlight | Smart recess surface downlight with integrated driver TW and dimmable



Areas of application

- Indoor applications
- Corridors, entrance areas, stairwells, living rooms, basements
- Bedrooms
- Kitchens

Product benefits

- $\,$ Creating individual light scenes according to your needs with cold white to warm white (3000 K to 6500 K)
- Surface downlight

Product features

- Controllable via SMART+ App (with minimum Android 8.0 or iOS 14.0) or any other Matter-compatible platforms
- Controllable via voice control available: Google Assistant or Amazon Alexa
- Adjustable color temperature via Tunable White: 3,000...6,500 K
- Dimmable
- Network protocol: Matter over WiFi (2.4 GHz)
- Housing material: metal

TECHNICAL DATA

Electrical data

Nominal wattage	22.00 W
Nominal voltage	220240 V
Mains frequency	5060 Hz
Nominal current	110.000 mA
Power factor λ	> 0.70
Total harmonic distortion	< 20 %
Protection class	1
Operating mode	External LED driver

Photometrical data

Luminous flux	1800 lm
Total luminous flux of contained light sources	2500 lm
Luminous efficacy	81 lm/W
Color temperature	30006500 K
Light color (designation)	Tunable White
Color rendering index Ra	≥80
Standard deviation of color matching	< 6 sdcm
Photobiological safety group acc. to EN62778	RG0
Beam angle	110°

Dimensions & Weight

Diameter	400.00 mm
Height	40.00 mm
Product weight	1270.00 g

SMART WIFI ORBIS DOWNLIGHT

Materials & Colors

Product color	White
Housing color	White
Body material	Aluminum
Cover material	Polycarbonate (PC)
Glow Wire Test according to IEC 60695-2-12	650 °C

Application & Mounting

Ambient temperature range	-2040 °C
Temperature range at storage	-20+70 °C
Type of connection	Screw terminal
Type of protection	IP20
Protection class IK (shock resistance)	IK03
Dimmable	Yes
Type of dimming	WiFi
Mounting type	Surface
Mounting location	Ceiling
Application environment	Indoor
With light source	Yes

Lifespan

Lifespan L70/B50 at 25 °C	25000 h
Number of switching cycles	15000

Emergency lighting

Type of emergency operation test	None
----------------------------------	------

Certificates & Standards

Standards	CE / UKCA
Ball shot safe	No
Replaceable light source (EPREL)	Not replaceable

Additional product data

Product remark	Available from October 2025 / Reset settings to default by switching the product on for five seconds and off for five seconds and repeating	
		this five times.

EQUIPMENT / ACCESSORIES

- For control via SMART+ App, a smartphone or tablet is required (with minimum Android 8.0 or iOS 14.0)
- Complete mounting and connecting accessories included

Safety advice

- All electrical connections must be made by a qualified person.
- Caution, risk of electric shock.
- Product in protection class I. All electrically conductive, metallic housing parts that can absorb voltage during operation or during maintenance in the event of a fault must be continuously connected to the protective earthing conductor.

DOWNLOAD DATA

	Documents and certificates	Document name	
POF	User instruction / safety instructions	SMART + WIFI ORBIS DOWNLIGH ROUND	
POF	Addon technical information	Wifi remote control compatibility list	
POF	Addon technical information	Wifi remote control compatibility list (DE)	
POF	Declarations of conformity	CE declaration SMART Matter Downlight	
PDF	Declarations of conformity UKCA	UKCA Declaration Orbis Spiral	
POF	Declarations of conformity UKCA	UKCA declaration SMART Matter Downlight	
POF	EU Data Act	SMART MATTER Lamps Luminaires Plugs	

LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4099854475634	Folding box	48 mm x 440 mm x 444 mm	1848.00 g	9.38 dm ³
4099854475641	Shipping box 5	459 mm x 268 mm x 472 mm	9240.00 g	58.06 dm ³

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

References / Links

- Further information and frequently asked questions (FAQs) at www.ledvance.com/en-int/home-lighting/services/faq

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.