

PRODUCT DATASHEET

LINK WIRELESS CONTROLLER 3 KEY UNV BLE

LEDVANCE LINK™ WIRELESS CONTROLLER | LEDVANCE LINK Wireless Controllers



Product features

- Commission and configure with LEDVANCE LINK™ app
- Control using either the LEDVANCE LINK™ app or the wireless controller
- Grouping and Zoning: Wirelessly group luminaires to act in sync with each other
- Scene Control: Preset various scenes for individual or group of luminaires using the app and/or wireless/wired controllers
- QR Code for Admin/Guest control: Using the LEDVANCE LINK™ app, Admin and Guest QR codes for each zone can be generated. Allows copying the settings to another phone/tablet by scanning this QR code
- Allows setting time-based schedules and high-end and low-end trim through the LEDVANCE LINK™ app

TECHNICAL DATA

Electrical data

Nominal voltage	120...277 V
Mains frequency	50...60 Hz

Dimensions & Weight

Length	102.87 mm
Width	43.18 mm
Height	41.91 mm
Product weight	84.00 g




Capabilities

Dimmable	Yes
----------	-----

Certificates & Standards

Protection class	N
Type of protection	IP66

DOWNLOAD DATA

	Documents and certificates	Document name
	Extended installation guide	BLUETOOTH MESH LINE VOLTAGE 3 BUTTON SWITCH USER MANUAL
	Extended installation guide	INSTALLATION GUIDE LEDVANCE LINKTM BLUETOOTH® LOW ENERGY MESH LINE VOLTAGE 3-BUTTON WALL CONTROLLER
	Extended installation guide	USER GUIDE LEDVANCE LINK FW Manager

LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4099854201202	Folding box 1			
4099854182464	Shipping box 40	480 mm x 250 mm x 280 mm	5845.00 g	33.60 dm ³

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.