

PRODUCT DATASHEET LINK SENSOR EXT PIR UNV BLE G2

LEDVANCE LINK™ HARDWIRED SENSOR | LEDVANCE LINK Hardwired Sensors



Product features

- Commission and configure with LEDVANCE LINK™ app
- Control using either the LEDVANCE LINK $^{\mbox{\tiny TM}}$ app or the wireless controller
- Grouping and Zoning: Wirelessly group luminaires to act in sync with each other
- Scene Control: Preset various scenes for individual or group of luminaires using the app and/or wireless/wired controllers
- QR Code for Admin/Guest control: Using the LEDVANCE LINK™ app, Admin and Guest QR codes for each zone can be generated. Allows
 copying the settings to another phone/tablet by scanning this QR code
- Allows setting time-based schedules and high-end and low-end trim through the LEDVANCE LINK™ app

TECHNICAL DATA

Electrical data

Nominal wattage	1.50 W
Nominal voltage	120277 V
Mains frequency	5060 Hz

Dimensions & Weight

Length	119.50 mm
Width	81.50 mm
Height	62.50 mm
Product weight	188.00 g

Additional product data

NAED	64163

Capabilities

Certificates & Standards

Protection class	N
Type of protection	IP65

DOWNLOAD DATA

	Spec Sheets and Product Documents	Document name
PDF	Extended installation guide	INSTALLATION GUIDE LEDVANCE LINK BLUETOOTH® LOW ENERGY MESH LINE VOLTAGE HIGHBAY SENSOR AND CONTROLLER
PDF	Extended installation guide	USER GUIDE LEDVANCE LINK FW Manager
PDF	Product information bulletin	DATASHEET LEDVANCE LINK BLUETOOTH® LOW ENERGY MESH LINE VOLTAGE HIGHBAY SENSOR AND CONTROLLER

LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4099854340529	Folding box	113 mm x 70 mm x 105 mm	244.00 g	0.83 dm ³
4099854325410	Shipping box 20	370 mm x 235 mm x 225 mm	5330.00 g	19.56 dm ³

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products.

When placing an order, for the quantity please enter single or multiples of a shipping unit.

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.